



MOSA GE S-8000 BBT ELECTRIC STARTER, AVR

Product price:

1.806,00 € tax excluded

Product description:

MOSA GES-8000 BBT 6,4 KW AVR

MOSA GES-8000 BBT is a three-phase generating set with a Briggs&Stratton gasoline-powered engine capable of delivering a power of 6.4 KW. The MOSA GES-8000 BBT generating set is equipped with electric start. The alternator of the MOSA GES-8000 BBT generator set is synchronous, three-phase, self-excited, self-regulated with class H insulation.

MOSA is compact and convenient to maneuver and transport thanks to its compact size, its weight of 112 kg as well as the practical tubular handles.

The MOSA GES-8000 BBT generator set with 20-liter tank has a fuel consumption of 2.7 liters/hour at 75% load for a range of more than 10 hours.

Sockets:

1x 400V 16A 3P+N+T CEE

1x 230V 16A 2P+T CEE

1x 230V 16A 2P+T Schuko

Technical specifications MOSA GES-8000 BBT:

Three-phase output Stand-by (LTP): 8 kVA (6.4 kW) / 400V /11.5A

Three-phase output PRP: 7 kVA (5.6 kW) / 400 V / 10.1A

Single-phase output: PRP 4 kW / 230 V / 17.4A

Frequency: 50 Hz

Cos ϕ : 0.8

MOTOR TECHNICAL DATA

Model: B&S - XR2100

Net stand-by output: 8.15 kWm (11 hp)

Net PRP output: 7. 3 kWm (10 hp)





Cylinders / Displacement: 1 / 420 cm³ (0.42 lt.)

Bore / Stroke: 90 / 66 (mm)

RPM Controller: Mechanical

110 % (Stand-by power): 4 lt. /h

100 % PRP: 200 g/kWh - 3.6 lt./h

75 % PRP: 200 g/kWh - 2.7 lt./h

50 % PRP: 220 g/kWh - 1.8 lt./h

Cooling system: Air

Sump oil capacity: 1.1 lt.

TECHNICAL DATA ALTERNATOR

Continuous power: 7 kVA

Standby power: 7.7 kVA

Single-phase voltage: 400 Vac

Frequency: 50 Hz

Cos ϕ : 1

Voltage regulation accuracy: ± 1 %

Sustained short-circuit current: 3 In

Transient Cdt (100% load): 15 %

Yield at 100% load: 82.5 % (400V - Cos ϕ 0.8)

Isolation: Class H

Connection - Terminals: Series - No. 6

Electromagnetic Compatibility (Radio Interference Suppression): EN55011

Harmonic Distortion - THD: Direct Synchronous - Xd: 222 %

Direct Transitory - X'd: 15 %

Direct Subtransitory - X''d: 4.7 %

Synchronous in quad. - Xq: 128 %

Transitory - T'd: 33 ms

Subtransitory - T''d: 6ms

Unloaded - T'do: 500 ms

Kcc short-circuit ratio: 0.72

Protection Class: IP 23

Cooling Air Flow: 0.06/ m³/sec

Coupling - Bearings: Direct J609b - No. 1

Voltage Regulator: AVR

AVR Model: HVR10

GENERAL SPECIFICATIONS

Tank capacity: 20 lt.

Run time (75% of PRP): 10.5 h

Starting battery: 12V - 18Ah (AE)

Measured acoustic power LwA (LpA pressure): 99 dB(A) (74 dB(A) @ 7m)

Performance class: G2Length: 770 mm

Width: 520 mm

Height: 650 mm





Weight: 112 Kg

Features:

- Electric start
- Engine stop for low oil level
- Magnetothermic switch
- Fuel level indicator
- Protective and partially hooded stretcher
- Silenced
- Portable
- Complies with CE safety directives
- AVR voltage regulator

If you are looking for another product such as MOSA GES-8000 BBT generator set then you can browse our catalog for more terrestrial generator sets.

Images and technical data are not binding.

.

Product features:

Phase: Single phase / Three phase

Continuous power single phase (KW): 4

Continuous power single phase (KVA): 5

Maximum power three phase (KW): 6.4

Continuous power three phase (KW): 5.6

Maximum power three phase (KVA): 8

Continuous power three phase (KVA): 7

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 x 400V 16A 3P+N+T CEE - 1 x 230V 16A 2P+T CEE - 1 x 230V 16A 2P+T SCHUKO

Engine: Briggs&Stratton XR2100, 4 stroke, OHV

Emissions Regulations: Stage 5

Engine rpm (rpm): 3000

Speed governor: Mechanical

Starting system: Elettrico

Engine capacity (cm³): 420

Number cylinders: 1

Oil capacity (L): 1.1

Cooling: Air





Alternator: Synchronous self-excited, self-regulated

Bore x stroke (mm): 90 x 66

Fuel tank capacity (L): 20

Consumption (L/h): 2.7 al 75% del carico

Running time (h): 7.4 at 75% of load

Acoustic pressure: 74 dB(A) at 7 m

Length (mm): 770

Width (mm): 520

Height (mm): 650

Dry weight (Kg): 112

Silenced: Yes

Super silenced: No

ATS Switch device : Optional

Voltage regulator: AVR