



GREEN POWER GP1650A/P OPEN (MANUAL CONTROL UNIT)

Product price:

200.836,00 € tax excluded

Product description:

The GREEN POWER 1500 rpm generators are designed for versatile use, from construction sites to industry, from agriculture to civil protection.

Robust welded steel frames with built-in tank of variable capacity produced by Green Power, engines and alternators supplied by the most important manufacturers in the sector and cutting-edge control units are the elements to ensure generators of excellent quality.

The hoods are made of steel, which allows them to be used in tropical environments. The Green Power covers guarantee maximum accessibility for maintenance and cleaning operations.

Green Power's strong point is the design and implementation within the company, a feature that helps to reduce the time to market of the product and allows any customization.

THIS PRODUCT IS ONLY AVAILABLE IN THE AUTOMATIC CONTROL UNIT VERSION

You can choose between the versions:

- Open group with AVR-Leroy alternator (automatic power pack)
- Open group with AVR-Mecc Alte alternator (automatic power pack)
- Open group with AVR-Stamford alternator (automatic power pack)

The image is purely indicative.





Product features:

Phase: Three phase
Maximum power three phase (KW): 1320
Continuous power three phase (KW): 1200
Maximum power three phase (KVA): 1650
Continuous power three phase (KVA): 1500
Fuel: Diesel
Frequency (Hz): 50
Voltage (V): 230 / 400
Engine: 1506A-E88TAG2
Emissions Regulations: NON EMISSIONATO
Engine rpm (rpm): 1500
Speed governor: Electronic
Starting system: Elettrico
Engine capacity (cm³): 45842
Number cylinders: 12
Cylinders' position: In line
Cooling: Water
Alternator: LINZ PRO 22SD/4 - Sincrono
Poles: 4
Protection degree: IP23
Fuel tank capacity (L): 800
Consumption (L/h): 237 Lt/h al 75% del carico
Running time (h): 3.37 h al 75% del carico
Length (mm): 5200
Width (mm): 2200
Height (mm): 2500
Dry weight (Kg): 12000
Silenced: No
Super silenced: No
ATS Switch device : Optional
Voltage regulator: AVR

