



CUMMINS C33 D5 THREE-PHASED DIESEL POWER GENERATOR 30KVA - OPEN

Product price:

7.718,00 € tax excluded

Product description:

CUMMINS C33 D5 Control system

Generator set control PowerStart 600

The PowerStart control is a microprocessor-based generator set monitoring and control system. The control provides a simple operator interface to the generator set, auto/ manual and remote start/stop control and shutdown fault indication. The integration of all control functions into a single control provides enhanced reliability and performance compared to conventional generator set control systems. This control has been designed and tested to meet the harsh environment in which gensets are typically applied.

- The PowerStart generator set control is suitable for use on a wide range of generator sets in nonparalleling applications. It is suitable for use with reconnectable or non-reconnectable generators, can be configured for either 50 Hz or 60 Hz and voltage and power connection from 190-600 VAC line-to-line.
- This control includes an intuitive operator interface that allows for complete genset control as well as system metering, fault annunciation, maintenance alarm, over imbalance current, configuration and diagnostics. The interface includes seven generator set status LED lamps with both internationally accepted symbols and English text to comply with customer needs. The interface also includes an LED backlit LCD display with tactile-feel softswitches for easy operation and screen navigation. The manual/auto/stop switch function is integrated into the interface panel.
- All data on the control can be viewed by scrolling through screens with the navigation keys. The control displays the current active fault and a timeordered history of the five previous faults.





- Power for this control is derived from the generator set starting batteries and functions over a voltage range from 8VDC to 16 VDC.

Product features:

Phase: Single phase / Three phase
Maximum power single phase (KW): 28.3
Continuous power single phase (KW): 25.7
Maximum power single phase (KVA): 28.3
Continuous power single phase (KVA): 25.7
Maximum power three phase (KW): 26.4
Continuous power three phase (KW): 24
Maximum power three phase (KVA): 33
Continuous power three phase (KVA): 30
Fuel: Diesel
Frequency (Hz): 50
Voltage (V): 230 / 400
Sockets configuration: Terminal box
Engine: 4 stroke
Emissions Regulations: Stationary Use
Engine rpm (rpm): 1500
Speed governor: Mechanical
Starting system: Electric
Engine capacity (cm³): 2500
Number cylinders: 4
Cylinders' position: In line
Cooling: Coolant Liquid
Alternator: Synchronous, brushless
Poles: 4
Bore x stroke (mm): 91.4x127
Length (mm): 1750
Width (mm): 923
Height (mm): 1240
Dry weight (Kg): 710
Silenced: No
Brushes: No
Product type: Generator
Control unit: PowerStart 600
ATS Switch device : Optional
Type of alternator: Constant Speed
Engine manufacturer: Cummins
Precision of voltage regulation: $\pm 2,5\%$

