



CGM C5000TE THREE- PHASE GENERATOR 5KVA

Product price:

1.777,50 € tax excluded

Product description:

CGM C5000TE Three-phase generator 5KVA

CGM C5000TE 5KVA Three-phase generator with Honda engine powered by STAGE V gasoline at 3000 rpm, compact and easy to use, mounted on a fixed base with rubber vibration dampers.

The CGM C5000TE generator is composed of a Made in Italy Linz or NSM alternator, self-excited with brushes and with AVR voltage regulator.

The CGM C5000TE generator is equipped with electric start with 12 V battery but also with manual recoil starter and with a low fuel consumption, in fact it consumes only 1,6 liters/hour at 75% of the load. This CGM C5000TE is perfect for outdoor use such as for hobby use.

The CGM C5000TE generator is part of the CLASSIC series and easily adapts to a variety of uses such as homes, mobile facilities, campgrounds, hobbies, construction sites, etc. The CGM C5000TE at 3000 rpm is suitable for emergency use only. It is not recommended for use for more than 6 hours continuously and for more than 500 hours per year.

Technical characteristics CGM C5000TE:

Type of phase: Singlephase / Threephase

Maximum singlephase power: 1.85 KVA / 1.6 KW

Continuous singlephase power: 1.7 KVA / 1.3 KW

Maximum threephase power: 5.5 KVA / 4.8 KW

Continuous threephase power: 5 KVA / 4 KW

Fuel: Petrol

Voltage: 230/400 V

Frequency: 50 Hz

Motor: HONDA GX270





Engine rpm: 3000 rpm
Starting: Electric
Voltage regulator system: AVR
Consumption: 1.6 Lt / h at 75% of load
Tank capacity: 5.3 Lt
Autonomy: 3.3 h at 75% of the load
Length: 780 mm
Width: 510 mm
Height: 500 mm
Weight: 80 Kg

Discover the full range reserved for generators of CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data are not binding.

Product features:

Phase: Single phase / Three phase
Maximum power single phase (KW): 1.6
Continuous power single phase (KW): 1.3
Maximum power single phase (KVA): 1.8
Continuous power single phase (KVA): 1.7
Maximum power three phase (KW): 4.8
Continuous power three phase (KW): 4
Maximum power three phase (KVA): 5.5
Continuous power three phase (KVA): 5
Fuel: Gasoline
Frequency (Hz): 50
Voltage (V): 230 / 400
Sockets configuration: 1 x 400V 16A 5P CEE - 1 x 230V 16A 3P CEE
Engine: Honda GX270
Emissions Regulations: Stage 5
Engine rpm (rpm): 3000
Starting system: Electric
Engine capacity (cm³): 270
Number cylinders: 1
Alternator: Made in Italy
Poles: 2
Fuel tank capacity (L): 5.3





Consumption (L/h): 1.6

Running time (h): 3.3

Length (mm): 780

Width (mm): 510

Height (mm): 500

Dry weight (Kg): 80

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : Optional

Voltage regulator: AVR

Engine manufacturer: Honda

