



CGM C13000T THREE- PHASE GENERATOR 12KVA

Product price:

2.520,00 € tax excluded

Product description:

CGM C13000T Three-phase generating set 12KVA

CGM C13000T Three-phase generator 12KVA with Briggs & Stratton engine powered by STAGE V gasoline at 3000 rpm, compact and easy to use, mounted on a fixed base with rubber vibration dampers.

The CGM C13000T generator is composed of a Made in Italy alternator from Linz or NSM, self-excited with brushes and with AVR voltage regulator.

The CGM C13000T generator is equipped with manual recoil start and low fuel consumption, in fact it consumes only 4.3 liters/hour at 75% of the load for an autonomy of up to 3 hours of operation.

This CGM C13000T is perfect for outdoor use such as hobby use. It is also available in a version with electric key start and with a panel for automatic start with ATS.

The CGM C13000T is part of the CLASSIC series and is easily adaptable to a variety of uses such as homes, mobile facilities, campgrounds, hobbies, construction sites, etc. The CGM C13000T generator set at 3000 rpm is suitable for emergency use only. It is not recommended to be used for more than 6 hours continuously and for more than 500 hours per year.

Technical specifications of CGM C13000T:

Type of phase: Singlephase / Threephase

Maximum singlephase power: 4.4 KVA / 3.5KW

Continuous singlephase power: 4 KVA / 3.2 KW

Maximum threephase power: 13.2 KVA / 10.5 KW

Continuous threephase power: 12 KVA / 9.6 KW





Fuel: Petrol
Voltage: 230/400 V
Frequency: 50 Hz
Motor: BRIGGS & STRATTON 18HP
Engine revolutions: 3000 rpm
Starting: Manual
Voltage regulator system: AVR
Consumption: 4.3 Lt / h at 75% of the load
Capacity tank: 8.5 Lt
Autonomy: 2 h at 75% of the load
Length: 910 mm
Width: 580 mm
Height: 640 mm
Weight: 111 Kg

Discover the full range reserved for generator of CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data are not binding.

Product features:

Phase: Single phase / Three phase
Maximum power single phase (KW): 3.5
Continuous power single phase (KW): 3.2
Maximum power single phase (KVA): 4.4
Continuous power single phase (KVA): 4
Maximum power three phase (KW): 10.5
Continuous power three phase (KW): 9.6
Maximum power three phase (KVA): 13.2
Continuous power three phase (KVA): 12
Fuel: Gasoline
Frequency (Hz): 50
Voltage (V): 230 / 400
Sockets configuration: 1 x 400V 32A 5P CEE - 1 x 230V 16A 3P CEE
Engine: Briggs&Stratton
Emissions Regulations: Stage 5
Engine rpm (rpm): 3000
Starting system: Manual
Engine capacity (cm³): 570
Number cylinders: 2





Alternator: Made in Italy

Poles: 2

Fuel tank capacity (L): 8.5

Consumption (L/h): 4.3

Running time (h): 2

Length (mm): 910

Width (mm): 580

Height (mm): 640

Dry weight (Kg): 111

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : No

Voltage regulator: AVR

Engine manufacturer: Briggs&Stratton

