



---

# PRAMAC ES3000 SINGLE PHASE AVR

Product price:

**708,00 € tax excluded**

## Product description:

PRAMAC ES3000 2.6 KW Single Phase Generator with AVR

PRAMAC ES3000 2.6 KW single phase generator with 3000 rpm petrol engine. The PRAMAC ES3000 generator is equipped with a manual recoil starter with automatic winding. The alternator of the PRAMAC ES3000 generator is equipped with brushes and an **AVR** voltage regulator. The AVR voltage regulator stabilizes the voltage, producing a cleaner and more stable current, thus protecting the sensitive devices connected. The Honda petrol engine makes the ES3000 AVR generator **very reliable** as it has been built and designed with top quality materials.

Thanks to its very low weight and **compact dimensions**, it is easy to transport where it is most needed. The PRAMAC ES3000 AVR single-phase generator is suitable for outdoor use on small construction sites or for small outdoor jobs for hobby use.

## Technical characteristics of the PRAMAC ES3000 AVR generator:

Maximum power Single-phase: 2.6 KW

Continuous use power Single-phase: 2.2 KW

Fuel: Petrol

Voltage: 230 V

Frequency: 50 Hz

Engine: Honda GX160

Starting: Self-recoil

Consumption: 1.2 Lt/h at 100% Load

Length: 623 mm

Width: 409 mm

Height: 500 mm

Weight: 43 Kg

AVR

## CONTROL PANEL





**Controls:**

- Switch: OFF - ON
- Ignition: Self-winding
- Fuel tap

**Standard protections:**

- Thermal protection
- Oil Guard (low oil level)

**Protections:**

- Thermal protection
- Oil Guard (low oil level)

**Sockets:**

N. 2 SCHUKO 230V 16A IP54

The PRAMAC ES3000 generator is a petrol generator developed by Pramac to guarantee a high level of quality and performance at an attractive price. The PRAMAC ES3000 generator is characterized by a robust structure with a tubular load-bearing frame and adequate steel sheet protections, with an oversized integrated tank.

The ES3000 generator is designed to satisfy long-lasting professional and intensive applications.

**If you are looking for a generator like the ES3000 AVR single-phase generator, we recommend that you consult our catalog of terrestrial generators to find the one that best suits your needs.**

Images and technical data are not binding. Always consult the technical data sheet provided by the manufacturer. Manel Service assumes no responsibility for any changes made by the manufacturer.

**Product features:**

Phase: Single phase

Maximum power single phase (KW): 2.6

Continuous power single phase (KW): 2.2

Maximum power single phase (KVA): 2.9

Continuous power single phase (KVA): 2.5

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 2 x 230V 16A IP54 SCHUKO

Engine: Honda GX160, naturally aspirated





Engine rpm (rpm): 3000  
Speed governor: Mechanical  
Ignition: Recoil  
Starting system: Pull starter  
Engine capacity (cm<sup>3</sup>): 163  
Oil capacity (L): 0.6  
Cooling: Air  
Alternator: With brushes  
Poles: 2  
Fuel tank capacity (L): 11  
Consumption (L/h): 0.9 at 75% of the load / 1.2 at 100% of the load  
Running time (h): 12.5 at 75% of the load / at 100% of the load  
Acoustic power: 96 dB(A)  
Acoustic pressure: 68 dB(A) at 7 m  
Length (mm): 623  
Width (mm): 409  
Height (mm): 500  
Dry weight (Kg): 43  
Silenced: No  
Super silenced: No  
Product type: Generator  
ATS Switch device : No  
Voltage regulator: AVR  
Engine manufacturer: Honda

