



---

# PRAMAC GSW50Y COFANATO CON QUADRO COMANDO MANUALE

## Product description:

## Product features:

Phase: Three phase

Maximum power three phase (KW): 37.03

Continuous power three phase (KW): 35.18

Maximum power three phase (KVA): 46.29

Continuous power three phase (KVA): 43.97

Fuel: Diesel

Frequency (Hz): 50

Voltage (V): 400

Sockets configuration: 1 x 400V 63A 3P+N+T - 1 x 400V 32A 3P+N+T CEE - 2 x 230V 16A 2P+T CEE - 1 x 230V 16A SCHUKO

Engine: Yanmar 4TNV98T-ZGPGE, turbocharged

Emissions Regulations: Stage 3A

Speed governor: Electronic

Starting system: Electric

Engine capacity (cm<sup>3</sup>): 3319

Number cylinders: 4

Cylinders' position: In line

Oil capacity (L): 11.2

Cooling: Water

Alternator: Mecc Alte ECO/P32-3S/4, brushless

Poles: 4

Fuel tank capacity (L): 68

Consumption (L/h): 8.3 at 75% of the load / 11.1 at 100% of the load

Running time (h): 8.2 at 75% of the load / 6.1 at 100% of the load





Acoustic power: 95 dB(A)  
Acoustic pressure: 66 dB(A) at 7 m  
Length (mm): 2000  
Width (mm): 920  
Height (mm): 1310  
Dry weight (Kg): 839  
Silenced: Yes  
Super silenced: Yes  
Product type: Generator  
ATS Switch device : No  
Voltage regulator: AVR  
Engine manufacturer: Yanmar

