



PRAMAC PX4000 2.7 KW generator set with AVR

Product price:

413,00 € tax excluded

Product description:

PRAMAC PX4000 2.7 KW AVR GENERATOR SET

The PRAMAC PX4000 single-phase 2.7 KW generator set is equipped with a petrol engine running at 3000 rpm. The PRAMAC PX4000 generator set features a manual recoil starter with a self-winding mechanism. The alternator of the PRAMAC PX4000 is equipped with an AVR voltage regulator. The Pramac petrol engine makes the PX4000 generator set highly reliable, as it is built and designed with high-quality materials.

Thanks to its very low weight and compact dimensions, it is easy to transport wherever it is needed most. The PRAMAC PX4000 single-phase generator is suitable for outdoor use on small construction sites or for small outdoor hobby jobs.

Technical characteristics of the PRAMAC PX4000 AVR generator set:

- Maximum single-phase power: 2.7 KW
- Continuous single-phase power: 2.3 KW
- Fuel: Petrol
- Voltage: 230 V
- Frequency: 50 Hz
- Engine: PRAMAC AP170F
- Starting: Recoil (manual pull start)
- Consumption: 1.29 Lt/h at 100% load
- Length: 600 mm
- Width: 439 mm
- Height: 588 mm
- Weight: 53 Kg
- Voltage regulator: AVR

CONTROL PANEL

Controls:





- Ignition key: OFF - ON

Instruments:

- Voltmeter
- Ammeter
- Frequency meter
- Fuel level indicator

Protections:

- Thermal protection
- Oil Guard (low oil level)

Sockets:

2 SCHUKO 230V 16A IP54

The PRAMAC PX4000 single-phase generator is a petrol generator and represents one of Pramac's latest innovations to ensure a high level of quality and performance at a competitive price. The PRAMAC PX4000 generator set is compact, efficient, and easy to use. It is perfect for all your semi-professional applications.

If you are looking for a generator set like the PRAMAC PX4000 AVR single-phase, we recommend consulting our catalogue of terrestrial generator sets to find the one that best suits your needs.

Product features:

Phase: Single phase

Maximum power single phase (KW): 2.7

Continuous power single phase (KW): 2.3

Maximum power single phase (KVA): 3

Continuous power single phase (KVA): 2.5

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 2 x 230V 16A IP54 SCHUKO

Engine: PRAMAC AP170F, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical

Starting system: Pull starter

Engine capacity (cm³): 208



Oil capacity (L): 0.6

Cooling: Air

Poles: 2

Fuel tank capacity (L): 18.5

Consumption (L/h): 0.96 at 75% of the load / 1.29 at 100% of the load

Running time (h): 19.27 at 75% of the load / 14.34 at 100% of the load

Acoustic power: 96 dB(A)

Acoustic pressure: 72 dB(A) at 7 m

Length (mm): 600

Width (mm): 439

Height (mm): 588

Dry weight (Kg): 53

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : No

Voltage regulator: AVR

Engine manufacturer: PRAMAC

Video: 0FIbtCzOIWA