



---

# PRAMAC S5000 SINGLE PHASE Generator set AVR

## Product price:

**1.700,00 € tax excluded**

## Product description:

Motore Honda Serie GX. Raffreddamento ad aria. Batteria fornita di serie. Protezione Oil Guard. Tubazioni telaio maggiorate. Serbatoio maggiorato. Bandelle laterali di protezione

L'immagine è puramente indicativa

## Product features:

Phase: Single phase

Maximum power single phase (KW): 4.8

Continuous power single phase (KW): 3.9

Maximum power single phase (KVA): 5.3

Continuous power single phase (KVA): 4.2

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration:

Engine: Honda GX270 Electric, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical

Starting system: Elettrico

Engine capacity (cm<sup>3</sup>): 270

Oil capacity (L): 1.1

Cooling: Air

Alternator: With brushes

Poles: 2





Fuel tank capacity (L): 26.5  
Consumption (L/h): 1.66 at 75% of the load / 2.21 at 100% of the load  
Running time (h): 15.96 at 75% of the load / 11.94 at 100% of the load  
Acoustic power: 97 dB(A)  
Acoustic pressure: 73 dB(A) at 7 m  
Length (mm): 840  
Width (mm): 615  
Height (mm): 753  
Dry weight (Kg): 89  
Silenced: No  
Super silenced: No  
Product type: Generator  
ATS Switch device : Optional  
Voltage regulator: AVR  
Engine manufacturer: Honda

