



PRAMAC S6000

Single/three-phase

Generator set 5.5KW

Product price:

2.627,00 € tax excluded

Product description:

Motore Honda Serie GX. Raffreddamento ad aria. Batteria fornita di serie. Protezione Oil Guard. Tubazioni telaio maggiorate. Serbatoio maggiorato. Bandelle laterali di protezione

L'immagine è puramente indicativa

Product features:

Phase: Single phase / Three phase

Maximum power single phase (KW): 2.56

Continuous power single phase (KW): 2.4

Maximum power single phase (KVA): 3.2

Continuous power single phase (KVA): 3

Maximum power three phase (KW): 5.5

Continuous power three phase (KW): 4.5

Maximum power three phase (KVA): 6.9

Continuous power three phase (KVA): 5.6

Fuel: Diesel

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration:

Engine: Yanmar L100N Electric, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical

Starting system: Elettrico

Engine capacity (cm³): 435





Oil capacity (L): 1.6

Cooling: Air

Alternator: Brushless

Poles: 2

Fuel tank capacity (L): 24

Consumption (L/h): 1.45 at 75% of the load / 1.94 at 100% of the load

Running time (h): 16.55 at 75% of the load / 12.37 at 100% of the load

Length (mm): 840

Width (mm): 641

Height (mm): 696

Dry weight (Kg): 124

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : Optional

Voltage regulator: Compound

Engine manufacturer: Yanmar

