



# PRAMAC S8000 THREE-PHASE Generator set + DPP, AVR

**Product price:**

**2.384,00 € tax excluded**

## **Product description:**

Motore Honda Serie GX. Raffreddamento ad aria. Batteria fornita di serie. Protezione Oil Guard. Tubazioni telaio maggiorate. Serbatoio maggiorato. Bandelle laterali di protezione

L'immagine è puramente indicativa

## **Product features:**

Phase: Single phase / Three phase

Maximum power single phase (KW): 3.2

Continuous power single phase (KW): 2.96

Maximum power single phase (KVA): 4

Continuous power single phase (KVA): 3.7

Maximum power three phase (KW): 6.6

Continuous power three phase (KW): 5.6

Maximum power three phase (KVA): 8.3

Continuous power three phase (KVA): 7

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 x 400V 16A 3P+N+T CEE - 1 x 230V 16A 2P+T CEE - 1 x 230V 16A SCHUKO

Engine: Honda GX390 Electric, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical

Starting system: Elettrico





Engine capacity (cm<sup>3</sup>): 389

Oil capacity (L): 1.1

Cooling: Air

Alternator: With brushes

Poles: 2

Fuel tank capacity (L): 26.5

Consumption (L/h): 2.14 at 75% of the load / 2.87 at 100% of the load

Running time (h): 12.33 at 75% of the load / 9.23 at 100% of the load

Acoustic power: 97 dB(A)

Acoustic pressure: 73 dB(A) at 7 m

Length (mm): 840

Width (mm): 615

Height (mm): 753

Dry weight (Kg): 112

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : Optional

Voltage regulator: AVR

Engine manufacturer: Honda

