



# PRAMAC SP12000 THREE-PHASE Generator set, AVR

**Product price:**

**4.375,00 € tax excluded**

## Product description:

Motore Honda Serie GX. Raffreddamento ad aria. Batteria fornita di serie. Protezione Oil Guard. Tubazioni telaio maggiorate. Serbatoio maggiorato. Bandelle laterali di protezione

L'immagine è puramente indicativa

## Product features:

Phase: Single phase / Three phase

Maximum power single phase (KW): 6

Continuous power single phase (KW): 5.44

Maximum power single phase (KVA): 7.5

Continuous power single phase (KVA): 6.8

Maximum power three phase (KW): 11.1

Continuous power three phase (KW): 9.4

Maximum power three phase (KVA): 13.8

Continuous power three phase (KVA): 11.8

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 x 400V 16A 3P+N+T CEE - 1 x 400V 32A 3P+N+T CEE - 3 x 230V 16A SCHUKO

Engine: Honda GX630, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical

Starting system: Elettrico





Engine capacity (cm<sup>3</sup>):

Oil capacity (L): 1.9

Cooling: Air

Alternator: Brushless

Poles: 2

Fuel tank capacity (L): 24

Consumption (L/h): 4.23 at 75% of the load / 5.63 at 100% of the load

Running time (h): 5.67 at 75% of the load / 4.26 at 100% of the load

Acoustic power: 96 dB(A)

Acoustic pressure: 72 dB(A) at 7 m

Length (mm): 960

Width (mm): 641

Height (mm): 667

Dry weight (Kg): 170

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : No

Voltage regulator: AVR

Engine manufacturer: Honda

