



# PRAMAC E5000 THREE PHASE

**Product price:**

**1.059,00 € tax excluded**

**Product description:**

Motore benzina Honda GX. Raffreddamento ad aria. Protezione Oil Guard. Avviamento a strappo. Alternatore sincrono. Robusta struttura con telaio tubolare portante. Prese su cuffia con protezioni termiche

L'immagine è puramente indicativa

**Product features:**

Phase: Single phase / Three phase

Maximum power single phase (KW): 3.04

Continuous power single phase (KW): 2.8

Maximum power single phase (KVA): 3.8

Continuous power single phase (KVA): 3.5

Maximum power three phase (KW): 5

Continuous power three phase (KW): 4.3

Maximum power three phase (KVA):

Continuous power three phase (KVA): 5.4

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 x 400V 16A 3P+N+T CEE IP44 - 1 x 230V 16A SCHUKO IP54 - 1 x 230V 16A 2P+T CEE IP44

Engine: Honda GX270 Recoil, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical

Ignition: Recoil

Starting system: Pull starter





Engine capacity (cm<sup>3</sup>): 270

Oil capacity (L): 1.1

Cooling: Air

Alternator: With brushes

Poles: 2

Fuel tank capacity (L): 5.3

Consumption (L/h): 1.6 at 75% of the load / 2.2 at 100% of the load

Running time (h): 3.2 at 75% of the load / 2.4 at 100% of the load

Acoustic power: 97 dB(A)

Acoustic pressure: 69 dB(A) at 7 m

Length (mm): 715

Width (mm): 540

Height (mm): 490

Dry weight (Kg): 70

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : No

Voltage regulator: Compound

Engine manufacturer: Honda

