



PRAMAC E8000 SINGLE-PHASE

Product price:

1.084,00 € tax excluded

Product description:

PRAMAC E8000 Single-phase 6.4 KW generator set

PRAMAC E8000 single-phase 6.4 KW generator set with Honda engine at 3000 rpm in open version. The PRAMAC E8000 single-phase generator set is equipped with a recoil starter with self-winding. The single-phase alternator of the PRAMAC E8000 generator set is brushless with a capacitor voltage regulator. The Honda engine makes this generator set **very reliable** as it is built and designed with high-quality materials.

Thanks to its frame, low weight and **compact dimensions** it is easy to transport where you need energy. The PRAMAC E8000 single-phase generator is suitable for outdoor use on small construction sites or for small outdoor jobs for hobby use.

Technical characteristics of the PRAMAC E8000 single-phase generator:

Maximum power Single-phase: 6.4 KW

Continuous use power Single-phase: 5.5 KW

Fuel: Petrol

Voltage: 230 V

Frequency: 50 Hz

Engine: Honda GX390 Recoil

Starting: Recoil

Consumption: 2.9 Lt/h at 100% load

Length: 750 mm

Width: 578 mm

Height: 531 mm

Weight: 72 Kg

CONTROL PANEL

Controls:

- Switch: OFF - ON
- Ignition: Self-winding
- Fuel tap





Standard protections:

- Thermal protection
- Oil Guard (low oil level)

Sockets:

N.1 SCHUKO 230V 16A IP54

N.1 2P+T CEE 230V 32A IP44

The PRAMAC E8000 generator is a petrol generator developed by Pramac to guarantee a high level of quality and performance at an attractive price. The PRAMAC E8000 generator is ideal for intense applications and is characterised by a robust structure with a load-bearing tubular frame, which simplifies both use and maintenance operations.

The E8000 generator is the essential generator to satisfy professional applications.

If you are looking for a generator like the PRAMAC E8000 single-phase generator, then we recommend that you browse our catalogue of terrestrial generators to find the one that best meets your needs.

Images and technical data are not binding.

Product features:

Phase: Single phase

Maximum power single phase (KW): 6.4

Continuous power single phase (KW): 5.5

Maximum power single phase (KVA): 7.2

Continuous power single phase (KVA): 6

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 1 x 230V 16A SCHUKO IP54 - 1 x 230V 32A 2P+T CEE IP44

Engine: Honda GX390 Recoil, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical

Ignition: Recoil

Starting system: Pull starter

Engine capacity (cm³): 389

Oil capacity (L): 1.1

Cooling: Air

Poles: 2

Fuel tank capacity (L): 6.1

Consumption (L/h): 2.1 at 75% of the load / 2.9 at 100% of the load

Running time (h): 2.9 at 75% of the load / 2.1 at 100% of the load





Acoustic power: 97 dB(A)
Acoustic pressure: 69 dB(A) at 7 m
Length (mm): 750
Width (mm): 578
Height (mm): 531
Dry weight (Kg): 72
Silenced: No
Super silenced: No
Product type: Generator
ATS Switch device : No
Voltage regulator: Capacitor
Engine manufacturer: Honda

