



PRAMAC ES3000 SINGLE-PHASE PETROL

Product price:

594,00 € tax excluded

Product description:

PRAMAC ES3000 Single-phase generator set 2.6 KW

PRAMAC ES3000 single-phase generator set of 2.6 KW with a petrol-powered engine at 3000 rpm. The PRAMAC ES3000 generator set is equipped with manual recoil starter with self-winding. The PRAMAC ES3000 generator set is brushless and has a voltage regulator with capacitor. The Honda petrol engine makes the ES3000 generator set **very reliable** as it has been built and designed using top quality materials.

Thanks to its very low weight and its **compact dimensions** it is convenient to transport where you need it most. The PRAMAC ES3000 single-phase generator is suitable for outdoor use on small construction sites or for small outdoor jobs for hobby use.

Technical characteristics of the PRAMAC ES3000 generator:

Maximum power Single-phase: 2.6 KW

Continuous use power Single-phase: 2.2 KW

Fuel: Petrol

Voltage: 230 V

Frequency: 50 Hz

Engine: Honda GX160

Starting: Recoil

Consumption: 1.2 Lt/h at 100% load

Length: 623 mm

Width: 409 mm

Height: 500 mm

Weight: 43 Kg

CONTROL PANEL

Controls:

- Switch: OFF - ON
- Ignition: Recoil start
- Fuel tap





Standard protections:

- Thermal protection
- Oil Guard (low oil level)

Protections:

- Thermal protection
- Oil Guard (low oil level)

Sockets:

N.2 SCHUKO 230V 16A IP54

The PRAMAC ES3000 generator is a petrol generator developed by Pramac to ensure a high level of efficiency, quality and performance at an attractive price. The PRAMAC ES3000 generator is characterized by a sturdy structure with a load-bearing tubular frame and adequate steel sheet protections with a built-in oversized tank. The ES3000 generator is designed to satisfy long-lasting professional and intensive applications. If you are looking for a generator like the single-phase ES3000 generator, we recommend that you browse our catalogue of terrestrial generators to find the one that best meets your needs.

Images and technical data are not binding. Please always consult the technical data sheet released by the manufacturer. Manel Service does not assume responsibility for any changes made by the manufacturer.

Product features:

Phase: Single phase

Maximum power single phase (KW): 2.6

Continuous power single phase (KW): 2.2

Maximum power single phase (KVA): 2.9

Continuous power single phase (KVA): 2.5

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 2 x 230V 16A IP54 SCHUKO

Engine: Honda GX160, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical

Ignition: Recoil

Starting system: Pull starter

Engine capacity (cm³): 163

Oil capacity (L): 0.6

Cooling: Air

Alternator: Brushless





Poles: 2

Fuel tank capacity (L): 11

Consumption (L/h): 0.9 at 75% of the load / 1.2 at 100% of the load

Running time (h): 12.5 at 75% of the load / at 100% of the load

Acoustic power: 96 dB(A)

Acoustic pressure: 68 dB(A) at 7 m

Length (mm): 623

Width (mm): 409

Height (mm): 500

Dry weight (Kg): 43

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : No

Voltage regulator: Capacitor

Engine manufacturer: Honda

