



---

# PRAMAC ES8000 THREE-PHASE PETROL GENERATOR

**Product price:**

**1.441,00 € tax excluded**

**Product description:**

Motore benzina Honda Serie GX. Raffreddamento ad aria. Protezione Oil Guard. Avviamento a strappo. Robusta struttura con telaio tubolare portante. Prese su cuffia con protezioni termiche. Serbatoio maggiorato. Bandelle laterali di protezione

L'immagine è puramente indicativa

**Product features:**

Phase: Single phase / Three phase

Maximum power single phase (KW): 3.2

Continuous power single phase (KW): 2.96

Maximum power single phase (KVA): 4

Continuous power single phase (KVA): 3.7

Maximum power three phase (KW): 6.6

Continuous power three phase (KW): 5.6

Maximum power three phase (KVA): 8.3

Continuous power three phase (KVA): 7

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 x 400V 16A 3P+N+T CEE IP44 - 1 x 230V 16A SCHUKO IP54 - 1 x 230V 16A 2P+T CEE IP44

Engine: Honda GX390 Recoil, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical





Ignition: Recoil

Starting system: Pull starter

Engine capacity (cm<sup>3</sup>): 389

Oil capacity (L): 1.1

Cooling: Air

Alternator: With brushes

Poles: 2

Fuel tank capacity (L): 11

Consumption (L/h): 2.1 at 75% of the load / 2.9 at 100% of the load

Running time (h): 5.1 at 75% of the load / 3.8 at 100% of the load

Acoustic power: 97 dB(A)

Acoustic pressure: 69 dB(A) at 7 m

Length (mm): 729

Width (mm): 500

Height (mm): 536

Dry weight (Kg): 81

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : No

Voltage regulator: Compound

Engine manufacturer: Honda

