



MOSA GE 8000 BBT

Product price:

1.099,00 € tax excluded

Product description:

MOSA GE8000 BBT 6,4 KW

MOSA GE8000 BBT is a three-phase generating set with a gasoline-powered engine capable of delivering a power of 6.4 KW. The MOSA GE8000 BBT generator set is equipped with a manual recoil starter. The alternator of the MOSA GE8000 BBT generating set is synchronous, three-phase, self-excited, self-regulated, brushless and with class H insulation. MOSA is compact and convenient to maneuver and transport thanks to its compact size, its weight of 79 kg as well as its practical tubular handles.

The MOSA GE8000 BBT generator set with 6.6-liter tank has a fuel consumption of 2.7 liters/hour at 75% load for an autonomy of up to 2 hours.

The control panel consists of:

- Output sockets: 1x 400V 16A 3P+N +T CEE / 1x 230V 16A 2P+T CEE
- Voltmeter
- Thermomagnetic circuit breaker
- Earth terminal (PE)

Technical specifications MOSA GE8000 BBT:

Single-phase output Stand-by (LTP): 8 kVA (6.4 kW) / 400V / 11.5A

Single-phase output PRP: 7 kVA (5.6 kW) / 400V / 10.1A

Single-phase output PRP: 4 kVA / 230V / 17.3A

Frequency: 50 Hz

Cos ? : 0.8

MOTOR TECHNICAL DATA

Model: B&S - XR2100

Net stand-by output: 8.1 kWm (11 hp)

Net PRP output: 7.3 kWm (10 hp)

Cylinders/Displacement: 1 / 420 cm³ (0.42 lt.)

Bore / Stroke: 90 / 66 (mm)

RPM Controller: Mechanical

FUEL CONSUMPTION





110 % (Stand-by power): 4 lt./h

100 % PRP: 3. 6 lt./h

75 % PRP: 2.7 lt./h

50 % PRP: 1.8 lt./h

Cooling system: Air

Capacity oil in sump: 1.1 lt

ALTERNATOR

Continuous power: 7 kVA

Standby power: 7.7 kVA

Single-phase voltage: 400 Vac

Frequency: 50 Hz

Cos ϕ : 0.8

Voltage regulation accuracy: ± 4 %

Sustained short-circuit current: 3 In

Transient Cdt (100 % of load): Efficiency at 100 % of load: 80. 5 % (400V - Cos ϕ 1)

Isolation: Class H

Connection - Terminals: Series - No. 6

Electromagnetic Compatibility (Radio Interference Suppression): EN55011

Harmonic Distortion - THD: Direct Synchronous - Xd 270 %

Direct Transitory - X'd 20 %

Direct Subtransitory - X "d 6. 5 %

Synchronous in quad. - Xq 150 %

Transitory - T'd 33 ms

Subtransitory - T "d 5.5 ms

Unloaded - T'do 450ms

Short-circuit ratio Kcc 0.60

Protection class: IP 23

Cooling air flow: 0.062/ m³/sec

Coupling - Bearings: Direct J609b - N°1

GOVERNMENTAL SPECIFICATIONS

Tank capacity: 6.6 l.

Range time (75% of PRP): 2.5 h

Acoustic power LwA (LpA pressure): 99 dB(A) (74 dB(A) @ 7m)

Performance class G2

Length: 770 mm

Width: 520 mm

Height: 650 mm

Weight: 79 Kg

MOSA GE8000 BBT portable generator set - Briggs&Stratton gasoline engine rewind start - Three-phase alternator - Three-phase power 7 kVA (5. 6 kW)

Features:





- Recoil start
- Motor complete with tank and muffler
- Engine stop for low oil level
- Alternator with Compound
- Circuit breaker
- LED voltmeter
- Fully protective open stretcher
- Portable
- Complies with CE safety directives

If you are looking for another product like the MOSA GE8000 BBT Generator Set then you can browse our catalog for more terrestrial generator sets.

Images and technical data are not binding.

Product features:

Phase: Single phase / Three phase

Continuous power single phase (KW): 3.2

Continuous power single phase (KVA): 4

Maximum power three phase (KW): 6.4

Continuous power three phase (KW): 5.6

Maximum power three phase (KVA): 8

Continuous power three phase (KVA): 7

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 x 400V 16A 3P+N+T CEE - 1 x 230V 16A 2P+T CEE

Engine: Briggs&Stratton XR2100, 4 stroke, OHV

Emissions Regulations: Stage 5

Engine rpm (rpm): 3000

Speed governor: Mechanical

Ignition: Recoil

Starting system: Pull starter

Engine capacity (cm³): 420

Number cylinders: 1

Oil capacity (L): 1.1

Cooling: Air

Alternator: Synchronous self-excited, self-regulated

Bore x stroke (mm): 90 x 66

