



ENDRESS ESE 506 DHS-GT Single-Phase / Three-Phase petrol generator

Product price:

1.297,00 € tax excluded

Product description:

Synchronous current generator with a compact 270 cc. Honda petrol engine, tear-off starter and a large 30 litre tank, which guarantees an autonomy of 18 hours!

ENDRESS ESE 506 HS-GT is equipped with an automatic stop system in case of lack of oil, overload protection, compound.

Suitable for supplying energy to :

- Power tools up to 4200 W
- Gardening tools up to 2900 W
- Compressors or pumps up to 2200 W

Images and technical data are not binding.

Product features:

Phase: Single phase / Three phase

Maximum power single phase (KW): 3.7

Continuous power single phase (KW): 2.8

Maximum power single phase (KVA): 4.2

Continuous power single phase (KVA): 3.1

Maximum power three phase (KW): 5

Continuous power three phase (KW): 4.3

Maximum power three phase (KVA): 6.3

Continuous power three phase (KVA): 5.4

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 1 x 400V 16A CEE - 1 x 230V 16A CEE





Engine: Honda GX270
Engine rpm (rpm): 3000
Starting system: Manual
Engine capacity (cm³): 270
Alternator: Synchronous
Poles: 2
Nominal current (A): 13.5
Fuel tank capacity (L): 30
Consumption (L/h): 1.6 at 75% of the load
Running time (h): 18 at 75% of the load / 13.5 at 100% of the load
Acoustic power: 97 dB(A)
Acoustic pressure: 72 dB(A) at 7 m
Length (mm): 800
Width (mm): 538
Height (mm): 576
Dry weight (Kg): 76
Silenced: No
Super silenced: No
Voltage regulator: Compound
Engine manufacturer: Honda

