



# LINZ E1E13M D Single-phase alternator 115V/230V 15 kVA 50 Hz AVR

## Product description:

The **SPE** and **E1E** series consist of single-phase 2-pole alternators with brushes and AVR electronic regulation.

## CHARACTERISTICS

- Compact and easy to assemble
  - High voltage accuracy
  - Wide range of accessories
  - AVR with built-in protections
  - Range: Single-phase alternators
  - Poles: 2
  - Phases: Single-phase
  - Adjustment: AVR
  - Application: PORTABLE
- Product available in 50 Hz and 60 Hz versions

Images and technical data are not binding.

## Product features:

Phase: Single phase  
Continuous power single phase (KW): 15  
Continuous power single phase (KVA): 15  
Frequency (Hz): 50 / 60  
Voltage (V): 115 / 230  
Engine rpm (rpm): 3000  
Alternator: Synchronous, brushless





Poles: 2

Single-phase power (KVA): 15

Protection degree: IP21

Motor insulation class: H

Length (mm): 495

Width (mm): 270

Height (mm): 379

Brushes: Yes

Type of alternator: Constant Speed

Voltage regulator: AVR

Weight (Kg): 77.7

