



LINZ E1C13S B/4 Single-phase alternator 115/230V 7 kVA 50 Hz 60 Hz Brushless

Product description:

LINZ E1C13/4 series are single-phase 4 poles brushless alternators with an auxiliary winding loaded on a capacitor regulating the voltage.

This series has been designed for application in light towers with metal halide, halogen lamps or LED.

CHARACTERISTICS

- Innovative rotating diode system
- Low harmonic content
- High efficiency

- Type: Single-phase alternators
- Poles: 4
- Phases: Single-phase
- Regulation: CAPACITOR
- Application: PORTABLE, LIGHTING TOWERS
product available in 50 Hz and 60 Hz versions

Product features:

Phase: Single phase

Continuous power single phase (KW): 7

Continuous power single phase (KVA): 7

Frequency (Hz): 50 / 60

Voltage (V): 115 / 230

Engine rpm (rpm): 1500





Alternator: Synchronous, brushless
Poles: 4
Single-phase power (KVA): 7
Protection degree: IP21
Motor insulation class: H
Length (mm): 405
Width (mm): 270
Height (mm): 379
Brushes: No
Type of alternator: Constant Speed
Voltage regulator: Capacitor
Weight (Kg): 50.5

