



LINZ E1X13S B/2 Three-phase alternator 277V/480V 12.5 kVA 60 Hz AVR

Product description:

E1X/2 series are three-phase brushless 2 poles alternators with exciter and electronic regulation (AVR).

CHARACTERISTICS

- Compact and mechanically resistant
- Minimum maintenance
- High efficiency

- Type: Three-phase alternators
- Poles: 2
- Phases: Three-phase
- Regulation: AVR
- Application: PORTABLE, TELECOMMUNICATION

Product features:

Phase: Three phase

Continuous power three phase (KW): 10

Continuous power three phase (KVA): 12.5

Frequency (Hz): 60

Voltage (V): 277 / 480

Engine rpm (rpm): 3600

Alternator: Synchronous





Poles: 2

Single-phase power (KVA): 12.5

Protection degree: IP21

Motor insulation class: H

Length (mm): 465

Width (mm): 270

Height (mm): 379

Brushes: No

Type of alternator: Constant Speed

Voltage regulator: AVR

Weight (Kg): 62

