



# LINZ E1X13S C/2 Three-phase alternator 230V/400V 12.5 kVA 50 Hz AVR

## Product description:

**E1X/2** series are three-phase brushless 2 poles alternators with exciter and electronic regulation (AVR).

## CHARACTERISTICS

- Compact and mechanically resistant
  - Minimum maintenance
  - High efficiency
  
  - Type: Three-phase alternators
  - Poles: 2
  - Phases: Three-phase
  - Regulation: AVR
  - Application: PORTABLE, TELECOMMUNICATION
- Product available in 50 Hz and 60 Hz versions

## Product features:

Phase: Three phase

Continuous power three phase (KW): 10

Continuous power three phase (KVA): 12.5

Frequency (Hz): 50 / 60





Voltage (V): 230 / 400

Engine rpm (rpm): 3000

Alternator: Synchronous

Poles: 2

Three-phase power (KVA): 12.5

Protection degree: IP21

Motor insulation class: H

Length (mm): 465

Width (mm): 270

Height (mm): 379

Brushes: No

Type of alternator: Constant Speed

Voltage regulator: AVR

Weight (Kg): 69

