



LINZ E1X13M D/2 Three-phase alternator 230V/400V 16 kVA 50 Hz 60 Hz AVR

Product description:

E1X/2 series are three-phase brushless 2 poles alternators with exciter and electronic regulation (AVR).

CHARACTERISTICS

- Compact and mechanically resistant
 - Minimum maintenance
 - High efficiency

 - Type: Three-phase alternators
 - Poles: 2
 - Phases: Three-phase
 - Regulation: AVR
 - Application: PORTABLE, TELECOMMUNICATION
- Product available in 50 Hz and 60 Hz versions

Product features:

Phase: Three phase

Continuous power three phase (KW): 12.8

Continuous power three phase (KVA): 16

Frequency (Hz): 50 / 60

Voltage (V): 230 / 400

Engine rpm (rpm): 3000





Alternator: Synchronous

Poles: 2

Three-phase power (KVA): 16

Protection degree: IP21

Motor insulation class: H

Length (mm): 554

Width (mm): 270

Height (mm): 375

Brushes: No

Type of alternator: Constant Speed

Voltage regulator: AVR

Weight (Kg): 86

