



GREEN POWER GP198S/D SOUNDPROOF (MANUAL CONTROL UNIT)

Product price:

25.052,00 € tax excluded

Product description:

The GREEN POWER 1500 rpm generators are designed for versatile use, from construction sites to industry, from agriculture to civil protection.

Robust welded steel frames with built-in tank of variable capacity produced by Green Power, engines and alternators supplied by the most important manufacturers in the sector and cutting-edge control units are the elements to ensure generators of excellent quality.

The hoods are made of steel, which allows them to be used in tropical environments. The Green Power covers guarantee maximum accessibility for maintenance and cleaning operations.

Green Power's strong point is the design and implementation within the company, a feature that helps to reduce the time to market of the product and allows any customization.

THIS PRODUCT IS ONLY AVAILABLE IN THE AUTOMATIC CONTROL UNIT VERSION

You can choose between the versions:

- Open group with AVR-Leroy alternator (automatic power pack)
- Open group with AVR-Mecc Alte alternator (automatic power pack)
- Open genset with AVR-Stamford alternator (automatic power pack)

The image is purely indicative.





Product features:

Phase: Three phase
Maximum power three phase (KW): 158.4
Continuous power three phase (KW): 144
Maximum power three phase (KVA): 198
Continuous power three phase (KVA): 180
Fuel: Diesel
Frequency (Hz): 50
Voltage (V): 230 / 400
Engine: DEUTZBF6M 1013FCG2
Emissions Regulations: Stage 2
Engine rpm (rpm): 1500
Speed governor: Electronic
Starting system: Elettrico
Engine capacity (cm³): 7146
Number cylinders: 6
Cylinders' position: In line
Cooling: Water
Alternator: MECC ALTE ECO38-1S/4
Poles: 4
Fuel tank capacity (L): 170
Consumption (L/h): 31.2 Lt/h al 75% del carico
Running time (h): 5.44 h al 75% del carico
Acoustic pressure: 68 dB(A)
Length (mm): 3300
Width (mm): 1100
Height (mm): 1770
Dry weight (Kg): 2130
Silenced: Yes
Super silenced: Yes
ATS Switch device : Optional
Voltage regulator: AVR

