



LINZ E1S11M AS KE Three-phase alternator 230V/400V 10 kVA 50 Hz 60 Hz AVR + Compound

Product description:

E1S-KE series are three-phase 2 poles alternators with brushes and mixed regulation: compound and electronic (AVR).

CHARACTERISTICS

- Possibility to feed any type of load
 - Compact and easy to assemble
 - High starting capacity
 - High efficiency
 - Type: Three-phase alternators
 - Poles: 2
 - Phases: Three-phase
 - Regulation: COMPOUND AND AVR
 - Application: PORTABLE
- product available in 50 Hz and 60 Hz versions

Product features:

Phase: Three phase

Continuous power three phase (KW): 8

Continuous power three phase (KVA): 10

Frequency (Hz): 50 / 60





Voltage (V): 230 / 400
Engine rpm (rpm): 3000
Alternator: Synchronous
Poles: 2
Single-phase power (KVA): 10
Protection degree: IP21
Motor insulation class: H
Length (mm): 415
Width (mm): 230
Height (mm): 325
Brushes: Yes
Type of alternator: Constant Speed
Voltage regulator: AVR+Compound
Weight (Kg): 45