



GENERATOR RENTAL 12KVA AVR

Product features:

Phase: Single phase / Three phase

Maximum power single phase (KW): 3.2

Continuous power single phase (KW): 2.6

Maximum power single phase (KVA): 4

Continuous power single phase (KVA): 3.3

Maximum power three phase (KW): 9.6

Continuous power three phase (KW): 8

Maximum power three phase (KVA): 12

Continuous power three phase (KVA): 10

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 CEE 5P 400V 16A + 1 CEE 3P 230V 16A

Engine: Honda GX690

Engine rpm (rpm): 3000

Starting system: Electric

Engine capacity (cm³): 688

Number cylinders: 2

Oil capacity (L): 1.9

Cooling: Air

Fuel tank capacity (L): 20

Consumption (L/h): 4.6 at 100% of the load

Running time (h): 4.34 at 100% of the load

Acoustic power: 92 dB(A)

Acoustic pressure: 67 dB(A)

Length (mm): 1070

Width (mm): 563

Height (mm): 921

Dry weight (Kg): 210

Silenced: Yes

Super silenced: Yes

ATS Switch device : No





Voltage regulator: AVR
Engine manufacturer: Honda

