



HONDA EU 20i Petrol Inverter Generator 2 kW 2.5 kVA

Product description:

Product features:

Phase: Single phase

Maximum power single phase (KW): 2

Continuous power single phase (KW): 1.6

Maximum power single phase (KVA): 2.5

Continuous power single phase (KVA): 2

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 2 x 230V SCHUKO

Engine: Honda GX100, 4 stroke, OHV

Engine rpm (rpm): 5000

Ignition: Transistorized

Starting system: Recoil

Engine capacity (cm³): 98.5

Number cylinders: 1

Oil capacity (L): 0.4

Cooling: Forced air

Alternator: Multipolar

Bore x stroke (mm): 56 x 40

Fuel tank capacity (L): 3.6

Consumption (L/h): 0.93

Running time (h): 3.83

Acoustic power: 89 dB(A)

Acoustic pressure: 71 dB(A)

Length (mm): 512

Width (mm): 290





Height (mm): 425

Dry weight (Kg): 20.7

Inverter: Yes

AVR: No

Compound: No

Silenced: Yes

Super silenced: Yes

Link Noleggio: <https://www.manelservice.com/eu-20i-2-5-kva/#noleggio>

