



SINCRO SK160 LA2 SINGLE-THREE-PHASE ALTERNATOR 28KVA AVR

Product description:

Three phase brushless alternator - AVR.

- Insulation class H
- IP23
- Standard voltage 230/400 V - 50 Hz
- Leads 6
- Bearings: Bearings are dimensioned for heavy duty
- Transient features: Transient voltage drop for rated step load at 0.8 power factor is less than 18%
- Single-phase operation: IB4 alternators can be connected for single-phase use
- Tropicalization: standard

Not binding images and technical data.

Product features:

Phase: Single phase / Three phase

Frequency (Hz): 50

Voltage (V): 230 / 400

Engine rpm (rpm): 3000

Poles: 2

Single-phase power (KW): 13.44

Single-phase power (KVA): 16.8

Three-phase power (KW): 22.4

Three-phase power (KVA): 28

Efficiency (%): 84.2





Shop name

Protection degree: IP23

Brushes: No

Type of alternator: Constant Speed

Voltage regulator: AVR

Weight (Kg): 97



PrestaShop