



RENTAL POWER GENERATOR CS18000T SINGLE-PHASE / THREE- PHASE STAGE V

Product description:

RENTAL GENERATOR CS18000T SINGLE-PHASE / THREE-PHASE STAGE V 19,2KVA

Rental Power Generator CS18000T three-phase of 19,2 KVA with BRIGGS & STRATTON engine power by STAGE V Gasoline at 3000 rpm, compact and easy to use.

The Rental CS18000T generator consists of an NSM Made in Italy, self-excited brushless alternator with **AVR** voltage regulator. The CGM CS18000T is equipped with electric start with battery that allows a practical and fast use even when cold. The CGM CS18000T has a low fuel consumption, in fact it consumes only 6,5 liters/hour at 75% of the load.

The Rental generator CS18000T is part of the QUIET series because thanks to the hood has low noise emissions and is supersilenced. This Rental generator is 3000 RPM, with BRIGGS & STRATTON engine with electric start with key and battery.

The rental service

Generator rental has never been easier: choose the product you want to rent and FILL OUT THE FORM .

Our specialized staff for the rental service will respond immediately with the most suitable offer for you!

The equipment available for rental can be shipped all over Italy and is always ready for action: our team of technicians ensures that it is always in perfect working condition.

It is advisable to book in advance for the rental of large quantities of machines: this is especially important in conjunction with trade fairs or events, where many people will use the rental service.





Technical features of the CS18000T:

Phase Type: Single-phase / Three-phase
Singlephase Continuous Power: 5.8 KVA / 4.6 KW
Singlephase Maximum Power: 6.4 KVA / 5.1 KW
Threephase Continuous Power: 17.5 KVA / 14 KW
Threephase Maximum Power: 19.2 KVA / 15.3 KW
Power Factor cos fi?: 0. 8
VAC voltage: 230 / 400 V
Frequency (Hz): 50
Voltage regulator: AVR
Start framework: Manual / Automatic
Engine: BRIGGS & STRATTON 31HP
RPM: 3000
Power supply: Gasoline
Emissions standard: STAGE V
Fuel tank capacity: 60 l
Fuel consumption @ 75 % load: 6.5 l/h
Autonomy @ 75 % load: 9.2 h
Sound pressure: 72 dB(A) @ 7m
Length: 1200 mm
Width: 730 mm
Height: 930 mm
Net weight: 280 Kg

Manual electric panel with:
n. 1 CEE 16A 3P 230V socket
n. 1 CEE 32A 5P 400V socket
General switch
connector for ATS
hour counter

Discover the full range of current generator on our catalog to find the one that best suits your needs.

Pictures and technical data not binding.

Product features:

Phase: Single phase / Three phase
Maximum power single phase (KW): 5.1
Continuous power single phase (KW): 4.6





Maximum power single phase (KVA): 6.4
Continuous power single phase (KVA): 5.6
Maximum power three phase (KW): 15.3
Continuous power three phase (KW): 14
Maximum power three phase (KVA): 19.2
Continuous power three phase (KVA): 17.5
Fuel: Gasoline
Frequency (Hz): 50
Voltage (V): 230 / 400
Sockets configuration: 1 x 230V 63A 3P CEE - 1 x 230V 16A 3P - 1 x 230V SCHUKO
Engine: BRIGGS & STRATTON 31HP
Emissions Regulations: Stage 5
Engine rpm (rpm): 3000
Starting system: Manual / Automatic
Engine capacity (cm³): 896
Number cylinders: 2
Cooling: Air
Alternator: NSM, made in Italy
Fuel tank capacity (L): 60
Consumption (L/h): 6.5 @ 75 % del carico
Running time (h): 9.2 @ 75 % del carico
Length (mm): 1200
Width (mm): 730
Height (mm): 930
Dry weight (Kg): 280
Silenced: Yes
Super silenced: Yes
Product type: Generator
ATS Switch device : Optional
Voltage regulator: AVR
Engine manufacturer: Briggs&Stratton
Video: MKDdx7hAnHc

