



---

# GENSET MG7.5 H-A Generator 7KVA STAGE V

**Product price:**

**2.561,48 € tax excluded**

**Product description:**

GENSET MG7.5 H-A GENERATOR 7KVA STAGE V

The GENSET Generator MG7.5 H-A 7KVA Stage V is a high-quality device designed to ensure reliable and durable performance. Equipped with a powerful Honda GX 390 OHV gasoline engine running at 3000 RPM and compliant with Stage V regulations, this model is perfect for a wide range of applications, both professional and domestic.

**Technical Specifications of the GENSET MG7.5 H-A 7KVA Stage V Generator:**

Maximum Power:

Single-phase: 2.5 KVA / 2 KW

Three-phase: 7 KVA / 5.6 KW

Voltage: 230 V - 400 V

Frequency: 50 Hz

Starting System: Electric

Engine: Honda GX 390 OHV, 390 cm<sup>3</sup>, 8.2 HP (6.1 kWm), air-cooled

Fuel Tank Capacity: 6.1 liters

Fuel Consumption: 3.3 liters/hour at 75% load

Dimensions: 725 mm (length) x 515 mm (width) x 585 mm (height)

Weight: 95 kg

**Features and Benefits**

The GENSET MG7.5 H-A Stage V Generator offers numerous features that make it an excellent choice:

Lifting Hook: Integrated into the frame for easy handling and transport.

Automatic Low Oil Shutdown: Protects the engine from potential damage.





### GENSET MG7.5 H-A 7KVA Stage V Electrical Outlets:

1 three-phase socket 16 A - 400 V

1 single-phase socket 16 A - 230 V

Integrated Safety Features: Differential thermal switch, power output protections, and voltmeter.

Connectivity: Connector for AMF-ATS panel and/or remote control.

Automatic Voltage Regulator (AVR): Maintains stable voltage to protect connected devices.

Protection Rating: IP23, offering a good level of protection against dust and water splashes.

The GENSET MG7.5 H-A Stage V is designed to operate in challenging environmental conditions, with an ambient temperature up to 40 degrees and altitudes up to 1000 meters. The sound power level is 99 dB (74 dB at 7 meters), ensuring relatively quiet operation for a GENSET MG7.5 H-A generator of this power.

The GENSET MG7.5 H-A 7KVA Stage V represents the ideal solution for those seeking a reliable, powerful, and versatile generator. With the Honda GX 390 OHV engine and automatic starting capability, this generator offers excellent performance in a compact and robust design. For both professional and domestic applications, the GENSET MG7.5 H-A 7KVA Stage V Generator is the perfect choice to ensure a constant and secure power source.

Looking for a generator with different features? [HERE](#) you can find the full range of GENSET products or other specialized brands in the industry.

Images and technical data are not binding and may be subject to revisions by the supplier.

#### **Product features:**

Phase: Single phase / Three phase

Maximum power single phase (KW): 2.5

Maximum power single phase (KVA): 2

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 x 400V 16A CEE - 1 x 230V 16A CEE

Engine: Honda GX390, 4 stroke, OHV

Emissions Regulations: Stage 5

Engine rpm (rpm): 3000

Starting system: Electric

Engine capacity (cm<sup>3</sup>): 390

Number cylinders: 1

Cooling: Air





Alternator: Synchronous  
Protection degree: IP23  
Motor insulation class: H  
Fuel tank capacity (L): 6.1  
Consumption (L/h): 3.3 at 75% of the load  
Acoustic power: 100 dB(A)  
Acoustic pressure: 74 dB(A) at 7 m  
Length (mm): 725  
Width (mm): 515  
Height (mm): 585  
Dry weight (Kg): 95  
Silenced: No  
Super silenced: No  
ATS Switch device : Optional  
Voltage regulator: AVR  
Engine manufacturer: Honda

