



# PRAMAC GBW22P Generator Set MCP Three- phase 17.6KW Enclosed with manual control panel

**Product price:**

**7.425,00 € tax excluded**

**Product description:**

PRAMAC GBW22P GENERATOR SET MCP THREE-PHASE 17.6KW

The PRAMAC GBW22P is a powerful three-phase generator set with 22 kVA output, designed to provide reliable emergency or backup power for a wide range of applications. Thanks to the Perkins 404J-22G engine and the Mecc Alte ECP28-M4 C alternator, this generator offers high performance and long service life.

Main features:

**Power:** With a maximum output of 22 kVA, this generator can supply power to a wide range of electrical devices, from small tools to larger equipment.

**Low noise:** Thanks to the soundproofing system, the noise level is extremely reduced, making it ideal for applications that require low acoustic impact.

**Compact and easy to handle:** Its compact dimensions and relatively light weight make the generator easy to transport and move.

**Reliable engine:** The Perkins engine is known for its robustness and reliability, ensuring long-lasting performance over time.

**Emission compliance:** The generator complies with Stage V emission standards, ensuring low environmental impact.

**Manual control panel:** The manual control panel allows easy management of all generator functions.





Versatile configuration: With multiple sockets, the generator can be connected to a wide variety of electrical devices.

Socket configuration:

- 400V 32A 3P+N+T CEE x 1
- 400V 16A 3P+N+T CEE x 1
- 230V 16A 2P+T CEE x 2
- 230V 16A SCHUKO x 1

**Technical specifications PRAMAC GBW22P THREE-PHASE:**

Phase type: Three-phase

Maximum three-phase power: 17.60 kW - 22 kVA

Continuous three-phase power: 16.10 kW - 20.12 kVA

Fuel: Diesel

Frequency: 50 Hz

Voltage: 400 V

Engine: Perkins 404J-22G

Speed governor: Mechanical

Starting system: Electric

Displacement: 2220 cm<sup>3</sup>

Cylinder arrangement: In-line

Oil capacity: 6 L

Cooling: Water

Alternator: Mecc Alte ECP28-M4 C

Number of poles: 4

Fuel tank capacity: 51 L

Fuel consumption at 75% load: 4 L/h

Autonomy at 75% load: 12.75 h

Sound power level: 95 dB(A)

Sound pressure level: 66 dB(A) at 7 m

Length: 1645 mm

Width: 870 mm

Height: 1060 mm

Dry weight: 546 kg

Looking for a generator similar to the PRAMAC GBW22P THREE-PHASE but with different technical specifications? [CLICK HERE](#) to explore our dedicated section for PRAMAC generators or other specialized brands.





**Product features:**

Phase: Three phase  
Maximum power three phase (KW): 17.6  
Continuous power three phase (KW):  
Maximum power three phase (KVA): 22  
Continuous power three phase (KVA):  
Fuel: Diesel  
Voltage (V): 400  
Sockets configuration: 1 x 400V CEE 32A | Morsettiera  
Engine: Perkins 404J-22G  
Emissions Regulations: Stage 5  
Speed governor: Mechanical  
Starting system: Elettrico / Automatico  
Engine capacity (cm<sup>3</sup>):  
Cylinders' position: In line  
Oil capacity (L): 6  
Cooling: Water  
Alternator:  
Poles: 4  
Fuel tank capacity (L): 51  
Consumption (L/h): 4 al 75% del carico  
Running time (h):  
Acoustic power: 95 dB(A)  
Acoustic pressure: 66 dB(A) at 7 m  
Length (mm): 1645  
Width (mm): 870  
Height (mm): 1072  
Dry weight (Kg):  
Silenced: Yes  
Super silenced: Yes  
Product type: Generator  
ATS Switch device : Optional  
Engine manufacturer: Perkins

