



PRAMAC GSW15Y HOOD WITH AUTOMATIC CONTROL PANEL

Product price:

12.056,25 € tax excluded

Product description:

PRAMAC GSW15Y ACP Three-phase 11.6 KW Super-Silent AVR Generator Set

PRAMAC GSW15Y three-phase generator set with 11.6 KW power, powered by a diesel engine running at 1500 RPM. The PRAMAC GSW15Y generator set is equipped with electric start. The three-phase alternator of the PRAMAC GSW15Y generator set is a brushless Mecc Alte with AVR voltage regulator. The AVR regulator stabilizes the voltage to prevent damage to connected sensitive devices. The Yanmar diesel engine makes the GSW15Y generator set very reliable as it is built and designed using high-quality materials.

Thanks to its casing, this generator set is super-silent. Additionally, it is easy to transport, install, and position due to its compact size, making this model ideal for emergency power supply, construction, mobile workshops, and industrial applications. The PRAMAC GSW15Y three-phase generator set is suitable for outdoor use on construction sites or for small professional outdoor jobs.

Technical specifications of the PRAMAC GSW15Y ACP Three-phase generator set:

- Maximum Three-phase power: 11.6 KW
- Continuous Three-phase power: 10.59 KW
- Fuel: Diesel
- Voltage: 400 V
- Frequency: 50 Hz
- Engine: Yanmar 3TNV88-BGPGE
- Start: Electric
- Consumption: 4 liters/hour at 100% load
- Length: 1800 mm
- Width: 850 mm
- Height: 1260 mm





- Weight: 580 Kg
- AVR

Automatic Control Panel ACP:

Integrated panel connected to the generator, with a microprocessor control module that gathers all command, control, and signaling electronic circuits. Direct switching control terminal board (ACP)

N.1 3P+N+T 400V 32A

The PRAMAC GSW15Y power generator is a professional diesel generator set developed by Pramac that offers many solutions for a variety of applications, from continuous use to emergency power supply. The PRAMAC GSW15Y power generator complies with safety and noise emission regulations and can be used in both residential and industrial environments.

The GSW15Y generator set is equipped with a reliable Yanmar diesel engine and various control panel solutions, supplements, and accessories that make it versatile and capable of meeting the most demanding customer needs.

If you are looking for a generator set like the GSW15Y ACP three-phase power generator, we recommend browsing our catalog of terrestrial generator sets to find the one that best suits your needs.

Images and technical data are not binding.

Product features:

Phase: Three phase

Maximum power three phase (KW): 11.6

Continuous power three phase (KW): 10.59

Maximum power three phase (KVA): 14.5

Continuous power three phase (KVA): 13.24

Fuel: Diesel

Frequency (Hz): 50

Voltage (V): 400

Sockets configuration: 1 x 400V 32A 3P+N+T CEE

Engine: Yanmar 3TNV88-BGPGE, naturally aspirated

Emissions Regulations: Stage 5

Speed governor: Mechanical

Starting system: Electric





Engine capacity (cm³): 1642
Number cylinders: 3
Cylinders' position: In line
Oil capacity (L): 6.9
Cooling: Water
Alternator: Mecc Alte ECP3-2L, brushless
Poles: 4
Fuel tank capacity (L): 68
Consumption (L/h): 3 at 75% of the load / 4 at 100% of the load
Running time (h): 22.8 at 75% of the load / 17.2 at 100% of the load
Acoustic power: 94 dB(A)
Acoustic pressure: 65 dB(A) at 7 m
Length (mm): 1800
Width (mm): 850
Height (mm): 1260
Dry weight (Kg): 580
Silenced: Yes
Super silenced: Yes
Product type: Generator
ATS Switch device : Optional
Voltage regulator: AVR
Engine manufacturer: Yanmar

