



PRAMAC S9000 THREE PHASE

Product price:

4.413,50 € tax excluded

Product description:

Motore Honda Serie GX. Raffreddamento ad aria. Batteria fornita di serie. Protezione Oil Guard. Tubazioni telaio maggiorate. Serbatoio maggiorato. Bandelle laterali di protezione

L'immagine è puramente indicativa

Product features:

Phase: Single phase

Maximum power single phase (KW): 3.04

Continuous power single phase (KW): 2.64

Maximum power single phase (KVA): 3.8

Continuous power single phase (KVA): 3.3

Maximum power three phase (KW): 8.2

Continuous power three phase (KW): 7

Maximum power three phase (KVA): 10.3

Continuous power three phase (KVA): 8.8

Fuel: Diesel

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 x 230V 32A 2P+T CEE - 1 x 230V 16A SCHUKO

Engine: Lombardini 25LD330, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical

Starting system: Electric

Engine capacity (cm³): 654

Oil capacity (L): 1.8

Cooling: Air





Poles: 2

Fuel tank capacity (L): 24

Consumption (L/h): 2.16 at 75% of the load / 2.90 at 100% of the load

Running time (h): 11.06 at 75% of the load / 8.25 at 100% of the load

Length (mm): 960

Width (mm): 641

Height (mm): 667

Dry weight (Kg): 160

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : Optional

Voltage regulator: Compound

Engine manufacturer: Lombardini

