



WFM SE12000-MTHE AVR

Product description:

Product features:

Phase: Single phase
Maximum power single phase (KW): 2.7
Maximum power single phase (KVA): 3.4
Fuel: Gasoline
Frequency (Hz): 50
Voltage (V): 230
Sockets configuration: 2 x 230V
Engine: Honda GX200
Engine rpm (rpm): 3000
Ignition: Recoil
Starting system: Pull starter
Engine capacity (cm³): 196
Number cylinders: 1
Oil capacity (L): 0.6
Cooling: Air
Fuel tank capacity (L): 3.6
Consumption (L/h): 1.6 at 100% of the load
Running time (h): 2.25 at 100% of the load
Acoustic power: 96 dB(A)
Acoustic pressure: 71 dB(A) at 7 m
Length (mm): 590
Width (mm): 390
Height (mm): 380
Dry weight (Kg): 40
Silenced: No
Super silenced: No
ATS Switch device : No
Voltage regulator: No





Shop name

Engine manufacturer: Honda



PrestaShop