



---

# WFM SE12000-MTHE AVR

## Product description:

### Product features:

Phase: Single phase / Three phase  
Maximum power single phase (KW): 1.8  
Maximum power single phase (KVA): 2.2  
Maximum power three phase (KW): 4.3  
Maximum power three phase (KVA): 5.4  
Fuel: Gasoline  
Frequency (Hz): 50  
Voltage (V): 230 / 400  
Sockets configuration: 1 x 400V CEE - 1 x 230V CEE  
Engine: Honda GX270  
Engine rpm (rpm): 3000  
Starting system: Electric  
Engine capacity (cm<sup>3</sup>): 270  
Number cylinders: 1  
Oil capacity (L): 1.1  
Cooling: Air  
Fuel tank capacity (L): 6.5  
Consumption (L/h): 2.4 at 100% of the load  
Running time (h): 2.7 at 100% of the load  
Acoustic power: 95 dB(A)  
Acoustic pressure: 70 dB(A) at 7 m  
Length (mm): 780  
Width (mm): 520  
Height (mm): 560  
Dry weight (Kg): 79  
Silenced: No  
Super silenced: No  
ATS Switch device : No





Shop name

---

Voltage regulator: No

Engine manufacturer: Honda



PrestaShop