



---

# WFM SE12000-MTHE AVR

## Product description:

### Product features:

Phase: Single phase  
Maximum power single phase (KW): 4.8  
Maximum power single phase (KVA): 6  
Fuel: Gasoline  
Frequency (Hz): 50  
Voltage (V): 230  
Sockets configuration: 1 x 230V - 1 x 230V CEE  
Engine: Honda GX390  
Engine rpm (rpm): 3000  
Ignition: Recoil  
Starting system: Pull starter  
Engine capacity (cm<sup>3</sup>): 389  
Number cylinders: 1  
Oil capacity (L): 1.1  
Cooling: Air  
Fuel tank capacity (L): 6.5  
Consumption (L/h): 3.1 at 100% of the load  
Running time (h): 2.09 at 100% of the load  
Acoustic power: 96 dB(A)  
Acoustic pressure: 71 dB(A) at 7 m  
Length (mm): 780  
Width (mm): 520  
Height (mm): 560  
Dry weight (Kg): 73  
Silenced: No  
Super silenced: No  
ATS Switch device : No  
Voltage regulator: AVR





Shop name

---

Engine manufacturer: Honda



---

PrestaShop