



---

# WFM SE12000-MTHE AVR

## Product description:

### Product features:

Phase: Single phase

Maximum power single phase (KW): 4.8

Maximum power single phase (KVA): 6

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 1 x 230V 16A 3P CEE - 1 x 230V 32A 3P CEE

Engine: Honda GX390, OHV

Engine rpm (rpm): 3000

Starting system: Electric

Engine capacity (cm<sup>3</sup>): 389

Number cylinders: 1

Oil capacity (L): 1.1

Cooling: Air

Fuel tank capacity (L): 15

Consumption (L/h): 3.1 at 100% of the load

Running time (h): 4.83 at 100% of the load

Acoustic power: 88 dB(A)

Acoustic pressure: 63 dB(A) at 7 m

Length (mm): 1100

Width (mm): 540

Height (mm): 650

Dry weight (Kg): 140

Silenced: Yes

Super silenced: Yes

ATS Switch device : Optional

Voltage regulator: AVR

Engine manufacturer: Honda



