



VINCO AG-HA-6500

Product description:

Product features:

Phase: Single phase

Maximum power single phase (KW): 4.2

Continuous power single phase (KW): 4

Maximum power single phase (KVA): 5.25

Continuous power single phase (KVA): 5

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 3 x 230V

Engine: CP188F, 4 stroke

Engine rpm (rpm): 3000

Starting system: Electric

Engine capacity (cm³): 389

Number cylinders: 1

Oil capacity (L): 1.1

Cooling: Air

Alternator: Synchronous

Fuel tank capacity (L): 25

Consumption (L/h): 2.31

Running time (h): 10.1

Acoustic power: 97 dB(A) a 4 m

Length (mm): 730

Width (mm): 590

Height (mm): 595

Dry weight (Kg): 78

Inverter: No

AVR: Yes

Compound: No

Silenced: No

Super silenced: No



