



VINCO AG-HA-6500

Product description:

Product features:

Phase: Single phase

Maximum power single phase (KW): 1.1

Continuous power single phase (KW): 1

Maximum power single phase (KVA): 1.38

Continuous power single phase (KVA): 1.25

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 2 x 230V

Engine: HY154F, 4 stroke

Engine rpm (rpm): 3100

Starting system: Pull starter

Engine capacity (cm³): 90

Number cylinders: 1

Oil capacity (L): 0.4

Cooling: Air

Alternator: Synchronous

Fuel tank capacity (L): 2

Consumption (L/h): 0.87

Running time (h): 2.3

Acoustic power: 95 dB(A) a 4 m

Acoustic pressure: 70 dB(A) at 7 m

Length (mm): 385

Width (mm): 525

Height (mm): 505

Dry weight (Kg): 23

Inverter: Yes

AVR: No

Compound: No

Silenced: No





Super silenced: No

