



VINCO AG-HA-6500

Product description:

Product features:

Phase: Single phase

Maximum power single phase (KW): 2

Continuous power single phase (KW): 1.8

Maximum power single phase (KVA): 2.5

Continuous power single phase (KVA): 2.25

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 2 x 230V

Engine: HY168FB, 4 stroke

Engine rpm (rpm): 3300

Starting system: Pull starter

Engine capacity (cm³): 196

Number cylinders: 1

Oil capacity (L): 0.6

Cooling: Air

Alternator: Synchronous

Fuel tank capacity (L): 3.85

Consumption (L/h): 1.1

Running time (h): 3.5

Acoustic power: 95 dB(A) a 4 m

Acoustic pressure: 70 dB(A) at 7 m

Length (mm): 415

Width (mm): 580

Height (mm): 530

Dry weight (Kg): 29.5

Inverter: Yes

AVR: No

Compound: No

Silenced: No





Shop name

Super silenced: No



PrestaShop